

Canon EOS-3 CUSTOM FUNCTION

E

CF	Function	NO.		Settings	
CF-0	Focusing screen characteristic	0		Ec-N, Ec-R	
		1		Ec-A, B, C, C II, D, H, I, L	
CF-1	Auto film rewind mode	0		High-speed	Yes → automatically
		1		REW	No → manually
		2		Quiet REW	Yes → automatically
		3			No → manually
CF-2	Film leader rewind position	0		Rewound in cartridge	
		1		Not rewound	
CF-3	Automatic DX-coded film speed setting	0		Enabled	
		1		Disabled	
CF-4	AF activation/AE lock method	0		Shutter button / AE lock button	
		1		AE lock button / Shutter button	
		2		Shutter button / Disabled (set during AF lock)	
		3		AE lock button / Disabled (real-time AE)	

CF-5	Main Dial / Quick Control Dial function in manual mode	0		Shutter speed / Aperture	
		1		Aperture / Shutter speed	
		2*1		Shutter speed / Aperture	
		3*1		Aperture / Shutter speed	
CF-6	Increments for Tv, Av, +/-	0		1/3-stop increments only	
		1		Full stops for Tv and Av, 1/3 stops for +/-	
		2		1/2-stop increments only	
CF-7	Full-time manual focusing in One-Shot AF mode	0		Enabled (with CF-4-1, 3, possible even before focus is achieved)	
		1		Disabled (with CF-4-1, 3, possible before focus is achieved)	
		2		Disabled (with CF-4-1, 3, not possible even before focus is achieved)	
CF-8	Frame counter sequence	0		Counts up	
		1		Counts down	
CF-9	AEB sequence / Auto cancellation	0		0 → — → + / Enabled	
		1		0 → — → + / Disabled	
		2		— → 0 → + / Enabled	
		3		— → 0 → + / Disabled	

*1: In the manual exposure and aperture-priority AE modes, the aperture can be set even without any lens attached.

CF-10	Focusing point superimposition	0		Enabled
		1		Disabled
		2		Enabled (no dim flashing)
		3		Bright flashing
CF-11	Focusing point selection method	0		< > + < >
				< > + < >
		1		< > + < >
				< > + < >
		2*2		< > Quick Control Dial operation only
				< > + < >
		3		< FEL > + < >
				< FEL > + < >
CF-12	Mirror lockup	0		Disabled
		1		Enabled
CF-13	Spot metering linkage (FE lock)	0		Center
		1		Linked to 11 focusing points
		2		Center (AF enabled at 11 focusing points)

CF-14	Automatic output reduction for fill-flash	0		Enabled
		1		Disabled
CF-15	Shutter-curtain synchronization	0		1st curtain sync
		1		2nd curtain sync
CF-16	Safety shift for Tv-AE and Av-AE	0		Disabled
		1	SS	Enabled
CF-17	Focusing point selection range	0		1 point (standard)
		1		1 point + immediately surrounding points
		2		1 point + automatic selection

*2:

1. If the < > button is pressed while the shutter button is pressed halfway, focusing point selection will be set to automatic.
2. The < > function is the combination of < > and < >.
3. The same operations as CF-11-1 are also possible with this setting.